

## General

Frequency Range	446.00625~446.09375
Channel Capacity	16
Channel Spacing	12.5kHz
Frequency Stability	±2.5PPM
Operating Temperature	-25~+55℃
Antenna Impedance	50Ω
Operating Voltage	DC7.4V
Dimension (H×W×D)	133×62×37mm
Weight (with antenna & battery)	230g
Battery	

## Transmitter

RF Power (H/L)	0.5W
Modulation Type	8kΦF3E
Modulation Limiting	≤2.5kHz
FM Distortion	≤5%
Residual FM	-35dB
Adjacent Channel Power	-60dB
Spurious and Harmonics	-36dBm ≤1GHz; -36dBm > 1GHz

## Receiver

Sensitivity	0.20μV
Adjacent Channel Selectivity	60dB
Intermodulation Reject Ratio	65dB
Spurious Response Reject Ratio	≥60dB
S/N	35dB
Rated Audio Power Output	≥600mW
Rated Audio Distortion	≤5%

### SHENZHEN HQT SCIENCE & TECHNOLOGY CO.,LTD.

ADD:5/F, East of Building M-8, Central Zone, Hi-tech Industrial Park,  
Nanshan District, Shenzhen, P.R.C. 518057

TEL: +86-755-86028800

FAX: +86-755-86028872

E-mail: export@hqt-tech.com.cn

[www.hqt-tech.com](http://www.hqt-tech.com)



All rights reserved to HQT. Pictures shown in this manual are for your reference only, if there is fluctuation, according to the real object, please.

Your Local Dealer



# TH-446Plus

Super-value Two-way Radio

## Best Choice For Elite Team



## Main Features

- Ergonomic & Robust Design
- Battery Power Inquiry
- Voice Encryption & Emergency Alert
- Voice Compandor & Noise Filter
- Whisper





# TH-446Plus

TH-446Plus is a compact-outlined professional two-way radio, embedded built-in voice compandor and noise filter, allowing easy and comfortable use. Its super-value functions are convenient and practical for coordination of scheduling and remote control.

## Main Features

### Eye-catching, Simple Outline

Compact outline, ergonomic design and anti-skid design make it comfortable to operate.

### 3 Programmable Keys

3 programmable keys can be programmed as desired functions by user.

### Power-on Battery Power Indication & Power Protection

Power on the radio and LED will indicate residual battery power L1, L2, L3, and L4 by flash times: 1, 2, 3 and 4. L1 means the battery power is low. The transmission will be inhibited to protect the radio when the supplied voltage is higher or lower than the required voltage.

### Auto Battery Save

When no signal is transmitted or received and no key is operated, several seconds later the radio will automatically enter battery save mode.



## Main Functions

### Voice Prompts

Voice prompts are available when switching channels and other function operation. This is specially designed for users such as work in the dim environment.

### Voice Encryption

It provides enhanced security to public communication and private communication because of effective prevention of wiretap on the same frequency.

### Whisper

Equipped with earphone you can speak quietly into the radio and still be heard clearly when this function is turned on.

### Emergency Alert

Users in emergency situations can turn on this function to emit local alarm tone or send SOS message to control center or pre-defined person.

### Monitor

You can press [MONI] key to hear a weak signal and it also helps adjusting volume when no signal is received.

### Battery Power Inquiry & Low Battery Alert

User could inquire residual battery power by pressing function key. If the battery power is insufficient, user would be reminded to charge it.

### VOX

Hands-free operation is available when VOX is on.

### PTT ID

With this function, ENI would be sent when pressing or releasing [PTT] key thus it provides identification of radio to control center.

### Scan

The radio begins scan every channel in scanning list when turn on this function.

### TOT

The feature allows for more efficient use of channels by limiting the amount of time of each transmission. Also, it effectively avoids radio damage because of long-time transmission.

### BCL

A channel is already in use is not available to others. It is used to prevent interference with the on-going conversation.

### CTCSS/CDCSS

The signalling can avoid unwanted conversations on the same channel.

### Wired Clone

To quickly set the parameters, you can clone the data from one radio to another one via standard clone cable.

### PC Programmable

Frequency and various features can be set by PC programming.



## Application

### Stock, Logistics Industry

light-weight, clear voice and long talk-time ensure user manage the condition with ease in busy and noisy environment, even in the underground warehouse where monitor function would help ensure smooth conversation.

### Hotel, Shopping Plaza, Super Market, Entertainment Places

light-weight feature and its VOX function can free your hands, so as to help you communicate and coordinate while provide considerate service to your customer. Whisper function enables you speak request quietly into the radio and still heard clearly, no worry to interfere the ardent conversations of customer.

### Manufacturing Industry

Noise filtering provides TH-446Plus more advantages in noisy working environment and thus effectively to ensure the successful completion of all work.

### Property Management, Enterprise Safety

Easy operation, clear voice, long talk-time and emergency alert can help safeguard successfully handle urgent events in very short time.



## Accessories



### Li Battery

BL1101  
Battery Capacity:  
1500mAh



### Charger Adapter

PS10001  
INPUT:100-240V~50/60Hz  
OUTPUT:12V 1000mA



### Charger

CL0600  
Charge Current:  
600mAh



### Belt Clip

S01  
Flexible Washer



### Ear-piece Mic

EHK01

### Other:

HK01 (Handed Mic&  
Speaker)  
Two-inline